

# Marantz CC-9100: Superb Sound Quality with Mega-Changer Convenience.



The Marantz CC-9100 300+1 disc CD changer combines advanced digital engineering for superb sonic performance with the unmatched convenience of mega-changer operation. The Marantz CC-9100 also makes it easy to organize a music library, letting you name, store and recall CDs by artist, title or custom playlists.

#### CC-9100 Features:

**300+1 disc capacity** provides up to 400 hours of music storage capacity. In addition, the CC-9100's handy single-disc loading feature allows the user to pop in another CD for instant playback.

**Quick disc access** is provided by the CC-9100's advanced carousel-type changer mechanism, engineered for smooth operation and unmatched reliability.

**Disc naming function** makes it easy to organize and access CDs. Each CD can be assigned a name that is displayed on the front panel whenever the CD is loaded, and CDs can be stored and filed by artist, title or in up to 10 custom playlists. Disc names can be entered using a standard PC keyboard or via the remote control.

**A variety of programming and play modes and convenience features** are provided, including "title" and "artist search" modes, favorite track programming and more.

**Convenient front panel jog wheel** provides easy disc selection.

**Precision optics and advanced D/A and digital filtering circuitry** deliver exceptionally accurate and natural CD sound that brings out the best in every music lover's CD collection.

**Compact design** only 17<sup>5</sup>/<sub>16</sub>" wide by 7<sup>5</sup>/<sub>8</sub>" high by 17<sup>1</sup>/<sub>8</sub>" deep allows easy integration into any home entertainment system or custom installation.

**Full remote control operation** of all functions including disc naming.

**D-BUS system connection** allows interface with other Marantz components for integrated operation of a complete Marantz system.

**Comprehensive front panel display** shows the status of your discs at a glance.

#### Audio Section

Frequency response	2 Hz - 20 kHz
Signal to noise ratio	>98 dB
Dynamic range	>96 dB
Total harmonic distortion	<.003%
Channel balance	<1.0 dB
Output voltage	2 Vrms

#### Inputs/Outputs

Audio output	2 (1L, 1R)
RC-5	1 in, 1 out
Optical digital output	1 toslink
PC keyboard input jack	1 front panel

#### General

Disc capacity	301
Power requirements	120 V, 60 Hz, 15 W
Dimensions W/H/D	17 <sup>5</sup> / <sub>16</sub> " x 7 <sup>5</sup> / <sub>8</sub> " x 17 <sup>1</sup> / <sub>8</sub> "
	440mm x 193mm x 434mm
Weight	17.2 lbs. 7.8 kg.

**marantz®**

Marantz America, Inc. 440 Medinah Road Roselle, IL 60172

Phone 630-307-3100 • Fax 630-307-2687 • [www.marantz.com](http://www.marantz.com)

Download from [www.Somanuals.com](http://www.Somanuals.com). All Manuals Search And Download.

## Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>