

8000Q

Pre - Amplifier

Specification

Reliable and robust, the 'Q' has been a stalwart of the 8000 series.

Good pre-amplifiers are few and far between in the audiophile world. To be considered such an audiophile pre-amplifier, the 8000Q must provide all of the functionality and control required without imparting any character of its own to the delicate audio signals.

It's this neutrality that is so hard to achieve, and it is this neutrality that is the secret of the 8000Qs enduring appeal.



8000Q	Input impedance	20 k nominal
	Input level vs. gain setting	500 mV at 0 dB - 350 mV at 3 dB - 250 mV at 6 dB 175 mV at 9 dB - 125 mV at 12 dB - 90 mV at 15 dB
	Frequency response (-3 dB)	0.1 Hz - 75 kHz
	Frequency response (± 0.2 dB)	20 Hz - 20 kHz
	Channel separation	greater than 100dB at 1 kHz
	Crosstalk rejection	greater than 100dB at 1 kHz
	Preamplifier output impedance	100 nominal
	Preamplifier maximum output	greater than 7.7 V rms (20 dBm)
	Record output impedance	1 k nominal
	Operating temperature range	greater than 10 - 35°C
	AC supply frequency	50 - 60 Hz
	AC supply voltage	110 - 120 V or 220 - 240 V
	Power consumption	less than 25 W
	Dimensions (WxHxD - mm)	445 x 74 x 335

Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>