


**BOSCH**

Invented for life

# FMM-100 Series Die-cast Metal Fire Alarm Manual Stations



- ▶ **Single or dual action**
- ▶ **Terminal connections**
- ▶ **Gold-plated alarm contacts for corrosion resistance**
- ▶ **Surface or weatherproof back boxes**

The FMM-100 Series is a family of versatile, high-quality, metal fire alarm manual stations. Single-action or dual-action models are available. All models come with a key lock and contain gold-plated contacts to resist corrosion.

## Functions

### Operation

#### Single-action

When the bar on the front of the manual station is pulled, it latches open and is easily visible from 50 ft (15 m). Reset the activation bar by opening the manual station with the key and placing the activation bar in its normal upright position. An optional scored acrylic break rod is available.

#### Dual-action

With the dual-action configuration the upper bar on the front of the manual station rotates inward allowing the activation bar to be grasped and operated by a single hand.

## Certifications and Approvals

Region	Certification
USA	UL UNIU: Boxes, Non-Coded (UL38), UNIU7: Boxes, Non-Coded Certified for Canada (cULus)
	CSFM 7150-1615: 224
	NYC-MEA 382-94-E or 382-94-E, Vol. 3

## Installation/Configuration Notes

### Compatibility Information

Compatible with all Bosch Security Systems, Inc. Fire Alarm Control Panels.

### Mounting Considerations

The FMM Series manual stations can be surface mounted on either the FMM-100BB-R Surface-mount Back Box or the FMM-100WPBB-R Weatherproof Back Box. They can also be flush mounted on a standard single-gang back box.

**Note** When properly mounted on the FMM-100WPBB-R Weatherproof Back Box, these manual stations meet UL requirements for outdoor use.

To comply with ADA standards, the manual station must be less than 48 in. (1.2 m) above the floor for front wheelchair access and less than 54 in. (1.3 m) above the floor for side wheelchair access.

**Parts Included**

Quant.	Component
1	Manual station
1	D102 Key (1358 key)
1	FMM-100GR Acrylic Break Rod
1	Hardware pack
1	Literature pack

**Technical Specifications**

**Environmental Considerations**

Relative Humidity:	90% at +100°F (+38°C)
Temperature (operating):	-40°F to +150°F (-40°C to +66°C)

**Mechanical Properties**

Color:	Red
Dimensions (H x W x D):	4.75 in. x 3.25 in. x 1.1 in. (12 cm x 8.3 cm x 2.8 cm)
Material:	die-cast metal

**Inputs**

Switch Rating:	1 A at 30 VDC or 125 VAC
----------------	--------------------------

**Ordering Information**

<b>FMM-100SATK Single-action Manual Station (red)</b> Versatile, high-quality, metal single-action fire alarm manual station with key lock and gold-plated contacts	<b>FMM-100SATK</b>
<b>FMM-100SATK-NYC Single-action Manual Station for New York City</b> Versatile, high-quality, metal single-action fire alarm manual station for New York City with key lock and gold-plated contacts	<b>FMM-100SATK-NYC</b>
<b>FMM-100DATK Dual-action Manual Station (red)</b> Versatile, high-quality, metal dual-action fire alarm manual station with key lock and gold-plated contacts	<b>FMM-100DATK</b>
<b>Accessories</b>	
<b>D102 Replacement Key</b> Replacement key (#1358) for the D101 lock.	<b>D102</b>
<b>FMM-100BB-R Surface-mount Back Box (red)</b> Red cast-metal back box	<b>FMM-100BB-R</b>
<b>FMM-100WPBB-R Weatherproof Back Box (red)</b> Red cast-metal weatherproof back box	<b>FMM-100WPBB-R</b>
<b>FMM-100GR Scored Acrylic Break Rods</b> Scored acrylic rods (12 per package)	<b>FMM-100GR</b>

**Americas:**  
Bosch Security Systems, Inc.  
130 Perinton Parkway  
Fairport, New York, 14450, USA  
Phone: +1 800 289 0096  
Fax: +1 585 223 9180  
security.sales@us.bosch.com  
www.boschsecurity.us

**Europe, Middle East, Africa:**  
Bosch Security Systems B.V.  
P.O. Box 80002  
5600 JB Eindhoven, The Netherlands  
Phone: +31 40 2577 284  
Fax: +31 40 2577 330  
emea.securitysystems@bosch.com  
www.boschsecurity.com

**Asia-Pacific:**  
Robert Bosch (SEA) Pte Ltd, Security Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6258 5511  
Fax: +65 6571 2698  
apr.securitysystems@bosch.com  
www.boschsecurity.com

## Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>