

FMM-462 Series POPIT Addressable Manual Stations

www.boschsecurity.com



BOSCH
Invented for life



- ▶ Single-gang mounting
- ▶ Latching alarm lever and key-locked reset
- ▶ Rugged die-cast housing with 14 gauge (1.9 mm) plated steel back and corrosion-resistant construction
- ▶ Optional scored acrylic breakrod

The FMM-462 Series Addressable Manual Stations allow people evacuating a building to initiate an alarm and alert others still inside. This UL-listed initiating device is compatible with the Bosch Security Systems, Inc. G Series Control Panels and the D9124 Fire Alarm Control Panel (FACP).

The POPIT module is addressed using on-board slide switches. It is then connected to a D9124 data expansion loop. The POPIT is polled by the control panel and sends reports on any opens, shorts, or ground faults on the manual station's wiring. The addressable feature allows the agencies responding to alarm or trouble conditions to go to the point that initiated the alarm or trouble report.

These low-profile manual stations are die cast with rounded edges to fit most design applications. All metallic components are painted or plated to inhibit corrosion. The FMM-462 Series Manual Stations conform with the Americans with Disabilities Act (ADA) standards.

Functions

Addressable Operation

The POPIT connects to a two-wire data expansion circuit from the control panel. Device address is set through slide switches on the POPIT Module, allowing programmable device identification by the control panel.

Certifications and Approvals

ADA	Complies with Americans with Disabilities Act ADA 4.28.3
NFPA	Complies with National Fire Protection Association NFPA 72

Region	Certification	
USA	UL	UNIU: Boxes, Non-Coded (UL38)
	CSFM	7150-1615:0122

Installation/Configuration Notes

Compatibility Information

The FMM-462 Series Addressable Manual Stations are compatible with the following products:

Category	Product ID	Product Description
Control	D7212G	Control panel
Panels:	D7412G	Control panel
	D9412G	Control panel
	D9124	Addressable FACP
Modules	D9127U	POPIT module

Mounting Considerations

The FMM-462 manual stations are for indoor use only. The FMM-462 or FMM-462-D and the wiring from the control panel data expansion loop fit into a single-gang back box for flush mounting. Use the larger FMM-100BB-R Back Box for surface mounting and to provide additional room for system wiring and the module.

Parts Included

Quant.	Component
1	Manual station
1	D9127U POPIT module
1	FMM-100GR scored acrylic breakrod
1	D102 Key (1358)
1	Literature pack

Technical Specifications

Environmental Considerations

Temperature (operating):	+14°F to +120°F (-10°C to +49°C)
--------------------------	----------------------------------

Mechanical Properties

Activation Force:	5 lb (2.3 kg)
Alarm Response Time:	1 sec (approximately)
Dimensions (HxWxD):	4.75 in. x 3.2 in. x 0.875 in. (12.1 cm x 8.1 cm x 2.2 cm)
Material:	Painted die-cast metal, plated steel back and painted steel front

Power Requirements

Current (alarm):	0.8 mA
Current (normal):	0.5 mA
Voltage (operating):	7 VDC to 15 VDC supplied by the control panel

Ordering Information

FMM-462 Single-Action Manual Station

A UL-listed initiating device compatible with the Bosch Security Systems, Inc. G Series Control Panels and the D9124 Fire Alarm Control Panel (FACP)
Order number **FMM-462**

FMM-462-D Double-Action Manual Station

A UL-listed initiating device compatible with the Bosch Security Systems, Inc. G Series Control Panels and the D9124 Fire Alarm Control Panel (FACP)
Order number **FMM-462-D**

Accessories

D102 Replacement Key

Replacement key (#1358) for the D101 lock.
Order number **D102**

FMM-100BB-R Surface-mount Back Box (red)

Red cast-metal back box
Order number **FMM-100BB-R**

FMM-100GR Scored Acrylic Break Rods

Scored acrylic rods (12 per package)
Order number **FMM-100GR**

Represented by:

Americas:

Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:

Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security
Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:

Bosch (Shanghai) Security Systems Ltd.
201 Building, No. 333 Fuquan Road
North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn

America Latina:

Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
al.securitysystems@bosch.com
www.boschsecurity.com

Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>